Total No. of pages 02 SECOND SEMESTER END SEMESTER EXAMINATION

ME104: Basic Mechanical Engineering

Time: 3 Hour Max. Marks: 50

Note: Answer any five questions from Part -A and five questions from Part-B. Assume suitable missing data, if any. Part-A & Part-B should be written in the same answer book separately

## PART-A

Q-1) Explain the followings –	<b>5</b> \
a) Thermodynamic equilibrium (1.	-
b) Perpetual motion machine of first and second kind (1.	
c) Specific weight, specific volume and specific gravity, Newton's law	of
	2)
Q-2 a) A turbine operates under steady flow conditions, receiving steam at t	he
following state: pressure 1.2MPa, temperature 188°C, enthalpy 2785 kJ/kg, veloc	ity
33.3m/s and elevation 3m. The steam leaves the turbine at the following sta	te:
pressure 20 kPa, enthalpy 2512 kJ/kg, velocity 100 m/s and elevation is zero. Heat	is
lost to the surroundings at the rate of 0.29kJ/s. If the steam flow through the turbi	ne
is 0.42kg/s, determine the power output of turbine in kW. (2.5)	5)
Q-2 b) If a gas of volume 6000 cm <sup>3</sup> and at pressure of 100kPa is compressed qua	•
statically according to $PV^2$ = constant until the volume becomes 2000cm <sup>3</sup> . Determine	ne
the work done. (2.	
Q-3a) A reversible heat engine operates between two reservoirs at temperature	•
600°C and 40°C. The engine drives a reversible refrigerator which operates between	on OI
reservoir at temperature of 40°C and -20°C. The heat transfer to the engine is 20°C.	NΛ
kJ and network output of the combined engine refrigerator plant is 360 kJ. Evaluation of the refrigerator plant is 360 kJ.	2)
the heat transfer to the refrigerant and net heat transfer to the reservoir of 40°C. (2.	
Q-3b) Prove that energy is a property of the system. (2.	
Q-4a) With the help of suitable P-V and T-s diagrams, explain the four processes of	ΣI
Otto cycle. Also derive the expression of efficiency of Otto cycle in term of	٠.
its compression ratio. (2	.5)
Q-4b) State and prove the Pascal's law. (2.	5)

Q-5b) What are the factors that are considered while selecting the site of ther power station. Explain them. (2 Q-6a) With the help of suitable diagram, explain the working of Pressurized W. Reactor. Also discuss the advantages and disadvantages of the same. (2 6b) Draw the suitable layout of Hydro power plant. List the four advantages and for the same of the same of the same of the same.	The sure (5) mal (5) ater (5)
PART-B	
Q-7-a) Explain briefly the following defects-blow holes, misrun, cold shut, hot to scab, in casting process with neat sketches. (2 Q-7-b) Explain briefly the investment casting process with neat sketch and	.5) its
Tr.	2.5)
Q- 8-a) Define the term "welding" and name the various welding technique. Differentiate between straight polarity and reverse polarity in electric arc welding (2)	
6	.5) ု
	.5)
Q-9-b) Differentiate between drilling and boring operation with neat sketches. (2 Q- 10-a) Explain briefly bending, drawing and metal spinning in metal form processes. (2.	ing <sub>(</sub>
Q-10-b) list the different types of comparator. Describe working principle of Sign comparator (Mechanical type) with a neat sketch.	
Q- 11-a) Classify the composite materials. Distinguish between particle reinforce and fibre reinforced composite. (2.5)	ed
Q- 11-b) Describe briefly spot resistance welding with a neat sketch and application.	•
Q- 12-a) Describe the different type of Plain carbon steel with their composition a	nd
its applications. (2.5 Q- 12-b) Draw a systematic diagram of a milling machine. Explain the different between face milling and peripheral milling. (2.5	ce
•	